

Epoc Solo™ Personal Panic Alarm



Professional Wireless Solutions



The Scope Epoc Solo is a rugged, compact, UHF Panic Alarm, with Lone Worker and Indoor Tracking capability*. It comprises a rechargeable UHF radio transceiver for sending both a primary and secondary message, together with a Bluetooth BLE module for indoor location reporting and tracking. The perfect hybrid solution for on-site security, school lockdown alert and personal protection.

IP67 Ingress Protection



Optional Wall Bracket



Features

- 25 mW RF output power
- Multi-colour LED array
- 2 button operation
- IP67 rugged case
- Li-ion Rechargeable
- Bluetooth BLE 5
- Lone Worker/Man Down
- Indoor Tracking*
- Optional wall bracket
- Optional desk charger
- Optional Programmer

See next page for further details

[*when used with Scope Blu Beacons]

Epoc Solo™ Personal Panic Alarm



Professional Wireless Solutions

Meet the Epoc Solo. The new addition to our Epoc family of critical communication responders and pagers

SPECIFICATIONS

Power:

Li-ion polymer 3.7V @850 mAh
Rechargeable battery

Dims: 97.4 (H) x 54.7 (W) x 16.7 (D) mm

Weight: 60 g approx.

Signal Format:

POCSAG FSK

Frequency:

438 - 470MHz

Channel Spacing:

12.5KHz or 25 KHz

Frequency Deviation:

+/-2.5KHz or +/-4.5KHz

RF Baud Rate:

512/1200/2400

Tx Performance:

25 mW RF power max

IOT: Bluetooth BLE V5.0

Compliance:

Radio Equipment Directive
2014/53/EU
ROHS Directive (EU) 2015/863

Standards Applied:

EN 300 220-1 V3.1.1 (Radio)
EN 301 489-1 V2.2.1 (EMC)
EN 62368-1: 2020 (Safety)

PANIC !



Send an SOS or Help message to Scope Epoc Blu responders or to Scope fixed transponders

ACK !



Transmit an Acknowledge indication back to the Epoc Solo LED array shows different colours for ACK OK and NO ACK

TRACK !



LOCATE !

Use with Scope Blu Beacons to identify location of user. Auto transmit to track user's movement

MAN DOWN !



Auto transmit a No Motion alarm after a preset lack of movement



Scope Communications UK Ltd
Quantum House
Steamer Quay
Totnes, Devon, TQ9 5AL
England


Tel: +44 (0) 1803 860700
Fax: +44 (0) 1803 863716
Web: www.scope-uk.com
Email: sales@scope-uk.com

Part Code: **EPOCLCHGUK**



Lite Charger with UK mains PSU

Part Code: **EPOCSPROG**



Programmer/Charger



Intelligent wall bracket sends a message when Epoc Solo is removed or inserted

Part Code: **ESBWCLIP**

Licensing: This equipment operates on licence-free SRD frequencies in the UK.
Contact our sales team for further details.

© Scope Communications UK Ltd. All specifications subject to change. E & OE.