

DA240

Signal line remote indicator

Powered by a signal line or independent source; this unit can indicate a change of signal. When the input signal is clear and acknowledged, the unit is silent with both LEDs off. When the signal goes to the alarm, the red LED comes on until the line is cleared and the sounder can be silenced by pushing the central button. When the signal is restored (alarm reset), the green light comes on with the sounder until the button has been pressed to acknowledge.

Input	
Voltage	10.5 to 14V DC
Connection type	PCB terminal block (2.5mm ²)
Environmental	
Operating temperature	-10°C to +40°C
Storage temperature	-20°C to +50°C
Operating relative humidity	Maximum 95% non-condensing
Dimensions*	
Width	148mm
Height	100mm
Depth	Head: 69mm Base: 60mm
Weight	< 0.8Kg
Enclosure material	Mild steel
Finish	Powder coated RAL 9016 (White)
Other	
Estimated mean time before failure (MTBF)	50,000 hours
CE Approved	Yes
Lid tamper	Yes
Internal battery	4.5V NiMH
CAUTION: Compatible battery packs should only be obtained from Dantech. Connecting alternative batteries (such as configurations of standard AA types) are likely to heat rapidly and explode.	

*(+/- 2mm)