

## ERA Plug In WiFi Door Chime



### Features

- The ERA Smarthome Plug-in WiFi Door Chime works with DoorCam
- Plug the Chime in any room to hear your doorbell
- Adjustable volume, or turn on/off Chime whenever you choose
- Optional light when doorbell rings
- Pair up to 4 Chimes to your DoorCam
- Choose a ringtone to suit you

Search for the free 'ERA DoorCam' App  
(must have DoorCam product)



### Packaging

**Contents:** 1 x ERA Plug In WiFi Chime, 1 x Manual

### Ordering Details

Product	Part No.
ERA WiFi Chime	ERA-WIFI-CHIME-W

### Technical Information

#### ERA Chime

Item	Parameter
Power Supply	UK Standard 230V AC
Power Range	230V AC +/- 10%
Power Consumption	3W (In use: Chime playing ringtone) 1W (Standby: installed well and chime not playing ringtone)
Antenna	Type: Internal PCB Antenna Gain: 2dBi (Max) Return Loss: Better or equal to -10dB
WiFi Connectivity	802.11 b/g/n
WiFi Encryption	WPA Personal WPA2 Personal
Speaker	8Ω/0.5W
Housing Material	PC Plastic
Operation Conditions	Temperature: 0°C ~ +40°C Humidity: ≤90% (non-condensing)
Dimensions (L x W x H)	75mm x 75mm x 68.5mm