Product data sheet



PM862

Power Supply Switch Mode 24VDC-2A

This efficiency cost effective power supply is ideal for use in Fire, Access control and general security applications.

Featuring a regulated 27.6 Vdc output supplying continuous full rated current to load plus additional current for charging two x 12V standby batteries.

The highly efficient switch mode design ensures low operating costs, generates less heat and with a small physical size increases the room available for additional PCBs or cables. The modular construction simplifies maintenance.



Details

- Fault and mains present indicators
- Battery disconnect to prevent deep discharge
- Tamperswitch
- Fault outputs
- Mains and dc fuse
- · Powder coated steel housing

PM862

Power Supply Switch Mode 24VDC-2A

Technical specifications

Electrical	220.1/4.6
Mains input	230 VAC
Output	
Power output voltage	27.6 VDC
Output ripple	100 mV pk-pk max.
Power output current	2 A
mains	
Battery	
Max. Battery capacity	7.2 Ah (x2)
Battery charge current	0.5 A
Battery recharge time	20 hours
Battery disconnect voltage	19.6 ±0.2 VDC
General	
Fuse(s)	230 VAC input 2 A, 12/24 V output 2 A
Physical	
Colour	White
Form factor	Steel cabinet
Standards & Regul	ation
Compliancy	CE, REACH, RoHS 2, WEEE
Input voltage	
	230 VAC
	50 Hz ±10%
Output voltage	
	27.6 VDC
Load output	
	1.5 A
Total output	
	2 A
Output ripple	
Output ripple	Max 100 mVrms
	Max. 100 mVrms
Max. battery size	
	7.2 Ah (x2)
Pottory reaboure 1	ma
Battery recharge ti	
	20
Battery disconnect	voltage
	19.6 ±0.2 VDC
Open collector out	put
	Open circuit on
	fault or mains fail
	- 0 V - 100 mA

Fuse 12/24 V outp	ut
	2 A
Fuse 230 VAC inp	ut
	2 A
Operating temper	ature
	-10 to +40°C
Relative humidity	
	95%
Housing (steel) po	owder coated
	1.2 mm
Dimensions (W x	H x D)
	330 x 275 x 80 mm

As a company of innovation, UTC Fire & Security reserves the right to change product specifications without notice. For the latest product specifications, visit UTC Fire & Security online or contact your sales representative.

