FERMAX

REF. 5204 READER PROX. DESKTOP AC-MAX KEY3-USB

Dimensions(width,height, depth) :30x88x12mm

USB desktop reader for registering 13.56MHz MIFARE cards in the AC-MAX system.

It can be used as an administrator reader to enter new card numbers in the access control application.

It includes a cable with a magnetic desktop support so it can be connected directly to the PC or through said support.

Once connected to the PC, the driver installation will start automatically. It does not require dedicated drivers.

FEATURES

Dimensions(width,height, depth) :30x88x12mm
Mounting: Sobremesa
Access Control System: AC-MAX
Reader operating mode: Tarjeta

Product weight (kg): 0,02 kg

TECHNICAL FEATURES

Standby consumption: 80 mA
Maximum consumption: 80 mA
Operating System: [5ºC,45ºC]
Humidity: [0%,95%]
Power Supply: USB
Maximun number of cards:
Cards type: Mifare 13.56Mhz
Nº of relays:

Maximum Relay Amperage (A):